

Atty Docket No. F0537

STRADDLED GATE FDSOI DEVICE

by

Zoran Krivokapic

CERTIFICATION UNDER 37 CFR 1.10

I hereby certify that the attached patent application (along with any other paper referred to as being attached or enclosed) is being deposited with the United States Postal Service on this date June 4, 2001, in an envelope as "Express Mail Post Office to Addressee" Mailing Label Number EL592220176US addressed to the: Box Patent Application, Commissioner for Patents, Washington, D.C. 20231.

David Friedman

(Typed or Printed Name of Person Mailing Paper)


(Signature of Person Mailing Paper)

STRADDLED GATE FDSOI DEVICE**TECHNICAL FIELD**

The present invention generally relates to the manufacture of semiconductor devices on semiconductor-on-insulator (SOI) structures and, more specifically, relates to the manufacture of fully depleted SOI (FDSOI) devices including a straddled gate for improving an off state (I_{off}) while maintaining a high on state (I_{on}).

BACKGROUND ART

Traditional silicon-on-insulator (SOI) and fully depleted SOI (FDSOI) transistor devices typically have a gate defining a channel interposed between a source and a drain formed within an active region of an SOI or FDSOI substrate. Such SOI or FDSOI devices have several advantages over devices formed on conventional bulk substrates: the elimination of latch-up, improved radiation hardness, dynamic coupling, lower parasitic junction capacitance, and simplified device isolation and fabrication. Such advantages allow semiconductor device manufacturers to produce low-voltage, low-power, high-speed devices thereon. For example, metal-oxide semiconductor field effect transistors (MOSFETs) are commonly formed on FDSOI structures. However, MOSFETs formed on such FDSOI structures suffer from a short-channel effect.

The short-channel effect refers to the effect caused by reducing a "long" channel to a "short" channel. A channel length is "long" where a depletion layer formed under the channel has a depth equal to its length. When a channel length is shortened to an extreme, the depletion layer extending from the drain side spreads in the direction of the source region and contacts with the depletion layer of the source side.

As a result, a potential barrier in the vicinity of the source is lowered by the drain voltage and a current (I_{off}) flows by itself even when no voltage is applied to the gate electrode. In this case, an energy band between the source and the drain changes continuously. This is the punch-through effect which lowers the withstand voltage between the source and the drain.

While various countermeasures have been taken to reduce the short-channel effect described above, a general measure, which has been taken most frequently, is channel-doping. Channel-doping is a technique for suppressing the short-channel effect by doping a trace amount of an impurity element such as P (phosphorus) or B (boron) shallowly in the channel region (as disclosed in Japanese Patent Laid Open Nos. Hei. 4-206971, 4-286339 and others).

However, the channel-doping technique has a drawback in that it significantly restricts the field effect mobility (hereinafter referred to simply as a mobility) of the MOSFET. That is, the movement of carriers is hampered by the intentionally doped impurity, thus dropping the mobility.

Therefore, there exists a need in the art for a device formed on a fully depleted semiconductor-on-insulator structure with increased performance and better characteristics enhanced by improving an off state (I_{off}) while maintaining a high on state (I_{on}).

SUMMARY OF THE INVENTION

According to one aspect of the invention, the invention is a straddled gate device formed on a semiconductor-on-insulator (SOI) substrate having active regions defined by isolation regions and an insulator layer. The device includes a first gate defining a first channel region interposed between a source and a drain formed within the active region of the SOI substrate. Additionally, the device includes a second gate straddling the first gate defining second channel regions interposed between the first channel region and the source and the drain. Further still, the device includes a contact connecting the first gate with the second gate wherein when the device is in the off state (I_{off}) the first channel region and second channel regions define a long channel and when the device is in the on state (I_{on}) the first channel region defines a short channel. In one embodiment, the device includes a silicide layer formed on the main source and drain regions.

According to another aspect of the invention, the invention is a straddled gate device formed on a germanium-on-insulator (GOI) substrate.

According to another aspect of the invention, the invention is a method of fabricating a straddled gate device formed on a semiconductor-on-insulator

(SOI) substrate having active regions defined by isolation regions and an insulator layer. The method includes the steps of forming a first gate defining a first channel region interposed between a source and a drain formed within the active region of the SOI substrate. Additionally, the method includes the step of forming a second gate straddling the first gate defining second channel regions interposed between the first channel region and the source and the drain. Further still, the method includes forming a contact connecting the first gate with the second gate wherein when the device is in the off state (I_{off}) the first channel region and second channel regions define a long channel and when the device is in the on state (I_{on}) the first channel region defines a short channel. In one embodiment, the method includes forming a silicide layer on the main source and drain regions.

BRIEF DESCRIPTION OF DRAWINGS

These and further features of the present invention will be apparent with reference to the following description and drawings, wherein:

FIG. 1 is a cross-section of a straddle gate FDSOI device including silicide layers according to the present invention;

FIG. 2 is a flow diagram of a method of manufacturing the straddle gate FDSOI device including silicide layers according to the present invention;

FIGS. 3A – 3P are cross-section views of the straddle gate FDSOI device including silicide layers according to the present invention at intermediate stages of manufacture.

DISCLOSURE OF INVENTION

In the detailed description that follows, identical components have been given the same reference numerals. To illustrate the present invention in a clear and concise manner, the drawings may not necessarily be to scale and certain features may be shown in a partial schematic format.

A straddle gate FDSOI device including silicide layers will now be described in accordance with the present invention. The device includes a first

gate and a second gate (straddle gate) straddling the first gate defining a channel interposed between a source and a drain disposed within an active region of a FDSOI structure. The active region is defined by isolation regions and an insulator layer. Further, the device includes a silicide layer formed on the main source and drain regions and silicide caps formed on the polysilicon spacers of the straddle gate as will be described in more detail below. Further still, the device may include contact plugs in electrical contact with the first gate and the straddle gate, and with at least one of the source and the drain.

A work function of the first gate and a work function of the straddle gate are uniquely defined. The work function of the straddle gate is less than the first gate. Thus, the straddle gate FDSOI device acts like a long channel in the off state (low I_{off}) and as a short channel in the on state (high I_{on}). Therefore, the straddle gate FDSOI device results in a device with improved I_{off} while maintaining a high I_{on} .

Referring initially to FIG. 1, a straddle gate FDSOI device of the present invention is shown generally designated as 10. The straddle gate FDSOI device 10 is formed within a fully depleted semiconductor-on-insulator (FDSOI) structure having a semiconductor substrate 12, an insulator layer 14 formed on the semiconductor substrate 12, and a semiconductor layer 13 disposed on the insulator layer 14. Within the semiconductor layer 13, isolation regions 16 as well as the insulator layer 14 define semiconductor active regions 18 of which one is shown in FIG. 1.

In an exemplary embodiment, as illustrated in FIG. 1, the active region 18 has an undoped region, or channel 20, and two N⁺ (source and drain) regions 22. The channel 20 is interposed between the source and drain regions 22. The source and drain regions 22 include respective deep implant regions 24 and 26, as well as respective extension regions 28 and 30. A gate dielectric 32 is interposed between a lower surface 34 of a gate electrode 36 and an upper surface 38 of the FDSOI semiconductor structure 40. The gate dielectric 32 illustrated in FIG. 1 is a multi-layer dielectric, however the gate dielectric could be a single-layer dielectric. The gate dielectric 32 includes a

lower dielectric layer 33 and an upper dielectric layer 35. The lower dielectric layer 33 may be made of suitable gate dielectric materials, such as silicon dioxide (SiO_2), silicon nitride (Si_3N_4), aluminum oxide (Al_2O_3), silicon oxynitride (SiON), or the like. The upper dielectric layer 35 may be made of high

5 permittivity (high k) gate dielectric materials, where a high-k value is generally greater than 3.9, such as hafnium oxide (HfO_2), zirconium oxide (ZrO_2), tantalum oxide (Ta_2O_5), or the like. In this embodiment, dielectric layer 33 is made of SiO_2 and dielectric layer 35 is made of HfO_2 . An exemplary dielectric layer 33 of SiO_2 may have a thickness of between 5 and 6 Å. An exemplary

10 dielectric layer 35 of HfO_2 may have a thickness of between 20 and 30 Å. The gate electrode 36 may be made of typical, well-known gate electrode materials, for example tungsten. An exemplary gate electrode 36 may have a thickness of between 500 and 700 Å.

Silicide layers 42, 44 are disposed on a portion of the source and drain regions 22. Silicide layers 42, 44 are formed over the respective deep implant regions 24 and 26. The silicide layers 42, 44 may be made of typical, well-known silicides, such as cobalt silicide (CoSi_2), titanium silicide (TiSi_2), tantalum silicide (TaSi_2), nickel silicide (NiSi_2) or the like. In an exemplary embodiment, the silicide layers 42, 44 are of CoSi_2 . Silicide layers 42, 44 could have a

5 thickness of between 200 Å and 400 Å.

On top of the semiconductor layer 13 and surrounding the silicide layers 42, 44 is an oxide layer 46. The oxide layer 46 may be made of the oxide materials described above within the gate dielectric materials. The oxide layer 46 may be made of the same oxide material as the thin dielectric layer 33 or

25 may be made of another oxide material described above. An exemplary oxide layer 46 may have a thickness of between 10 and 12 Å. The oxide layer 46 in this embodiment is made of silicon dioxide (SiO_2). It will be understood that the use of the term oxide with regard to the oxide layers or portions thereof, encompasses the variety of suitable well-known materials for protecting the

30 underlying surface material, e.g. the gate electrode.

A nitride layer 48 is formed on the oxide layer 46 as well as the sidewalls of the gate electrode 36. The nitride layer 48 may be made of silicon nitride (Si_3N_4), silicon oxynitride (SiON), or the like. An exemplary nitride layer 48 may have a thickness of about 10 Å. The nitride layer 48 in this embodiment is made of silicon nitride Si_3N_4 .

Spacers 50 extend upward from the upper surface 52 of the nitride layer 48 and cover the sidewalls of the nitride layer 48 formed on the sidewalls of gate electrode 36. The spacers 50 extend substantially above the top of the gate electrode 36. Exemplary spacers 50 may have a height of between 800 Å and 1000 Å and a width between 250 Å and 350 Å. The spacers 50 may be made of polysilicon, or the like.

Silicide caps 56 are disposed on top surfaces of the spacers 50. Silicide caps 56 may be made of typical, well-known silicides, as described above. In an exemplary embodiment, the silicide caps 56 are of CoSi_2 . Silicide caps 56 could have a thickness of between 100 Å and 400 Å.

Interposed between spacers 58 and a portion of the nitride layer 48 and spacers 50 are liner oxide layers 60. The liner oxide layers 60 also surrounds the silicide layers 42, 44. The liner oxide layers 60 also cover a portion of the sidewalls of the spacers 50. Spacers 58 extend upward from the upper surface 62 of the liner oxide layers 60 and cover the sidewalls of the liner oxide layers 60 formed on the portion of the sidewalls of the spacers 50. The spacers 58 extend substantially to the top of the sidewalls of the liner oxide layers 60. Exemplary spacers 58 may have a width of between 400 Å and 600 Å. The spacers 58 may be made of nitride, or the like.

As illustrated in FIG. 1, an isolation layer 64 is formed over the above described structure. The isolation layer may be made of tetraethylorthosilicate (TEOS), or the like. Exemplary TEOS layer 64 may have a thicknesses between 800 and 1000 Å.

Within TEOS layer 64, contact plugs 80, 82 are formed. Contact plugs 80 are formed in the TEOS layer 64 over the source and drain regions 22. As is known in the art, the contact plugs 80 establish an electrical connection to

the source and drain regions 22. Instead of the contact plug shown, metal layers (not shown) could be formed in the TEOS layer 64 to establish electrical connection to the source and drain regions 22. V_{sense} , V_{bit} , V_{word} , or other electrical connections may be established to the contact plugs 80, gate electrode 36 and the polysilicon spacers 50, respectively. As shown in FIG. 1, a contact plug 82 is formed in the TEOS layer 64 over the gate electrode 36, the polysilicon spacers 50, the liner oxide layers 60 and the spacers 58, respectively. The contact plugs 80, 82 can also be used along with any contacts and metal layers to establish electrical connection between other nodes (such as an I/O pad or V_{ss}), source or drain of the device.

A variety of materials can be used for the contact plugs 80, 82 including single metal layers as well as metal alloy layers containing two or more metals. One such appropriate metal is tungsten. Tungsten has a high melting temperature, which allows it to endure high-temperature manufacturing processes such as annealing, for example, as described below.

It will be appreciated that other suitable metals may alternatively or in addition be used for the contact plugs 80, 82. For example, layers of different types of metals may be used, if desired. Alternatively, alloys or other combinations of suitable metals may be employed. Alternative examples of other materials include aluminum, nickel, palladium, platinum, tantalum, titanium, aluminum alloys, titanium alloys, tungsten alloys, titanium-tungsten alloys, nickel alloys, palladium alloys, platinum alloys, tantalum alloys, metal silicides, and any other alloys thereof. The advantageous property of high electrical conductivity of a metal contact plugs 80, 82 makes for lower resistance connections between the gate electrodes 36, 50 and other electrical components of the straddled gate FDSOI device 10. However, it will be appreciated that suitable non-metallic semiconductor materials, such as silicon, may alternatively be employed in the contact plugs 80, 82 if desired.

Interposed between the contact plugs 80, 82 and the aforescribed structure are diffusion barriers 86. The diffusion barriers 86 may be made of,

for example, titanium nitride (TiN) or the like. Exemplary diffusion barriers 86 may have thicknesses between 50 and 150 Å.

It will be appreciated that the active region 18, the channel 20, the source and drain regions 22, the gate dielectric 32, the gate electrode 36, spacers 50 with the silicide caps 56, the silicide layers 42, 44, and the contacts 80, 82 together form the straddle gate FDSOI device of the present invention. The principles of operation of a straddle gate FDSOI having silicide layers over the source and the drain regions of the gate device will be further explained below. It will be appreciated that the straddle gate FDSOI device 10 may alternatively have other shapes than the shape shown in FIG. 1.

The steps of a method 210 for fabricating a semiconductor device 310 (which may be similar to the semiconductor device 10 described above) are outlined in the flow chart shown in FIG. 2. FIGS. 3A-3C illustrate various steps of the method 210. It will be appreciated that the method 210 and the semiconductor device 310 described below are merely exemplary, and that suitable embodiments of the many above-described variations in materials, thicknesses, and/or structures may alternatively be used in the method 210 and/or the semiconductor device 310.

In step 212, a FDSOI structure 340 is formed as represented in FIG. 3A. A wafer bonding technique described below may form the FDSOI structure 340. An insulator layer 314 is formed on a first semiconductor substrate 312 (handler substrate). The handler substrate may be of silicon, germanium, or other similar semiconductive material. For the exemplary embodiment a silicon substrate is used. The insulator layer can be any oxide such as silicon dioxide (SiO₂), aluminum oxide (Al₂O₃), silicon oxynitride (SiON), or the like or any other material with insulator properties such as undoped polysilicon or the like. A chemical or thermal process may be used to form the oxide layer. In one embodiment, a silicon dioxide is thermally grown on the handler substrate 312. Next, a second wafer (not shown), e.g. of silicon, germanium, or other similar semiconductive material, has an insulator layer, e.g. an oxide, such as silicon dioxide chemically vapor deposited (CVD) thereon. The oxide layer may also be

thermally grown as described above. Then, one of the substrates, e.g. the second wafer, is flipped over such that the oxide layers are in contact. The second wafer with the oxide layer is then wafer bonded to the handler substrate 312 with the oxide layer at the SiO₂ interface. Well-known techniques such as, Bonded and Etchback (BESOI) or the Smart-Cut may be used to reduce the second wafer to a thin semiconductive layer 313. A thermal fusing process may be used at this time to more securely fuse the FDSOI structure. If a semiconductive substrate of germanium is used a silicon oxide or the like is used due to germanium oxide being unstable. Thus, the resulting FDSOI structure 340 includes the semiconductor substrate 312 (handler substrate), an insulator layer 314 formed on the semiconductor substrate 312 and a semiconductor layer 313 disposed on the insulator layer 314 as described above. An exemplary insulator layer 314 may have a thickness of between 1000 Å and 3000 Å. Whereas, an exemplary semiconductor layer 313 disposed on the insulator layer 314 may have a thickness of between 800 Å and 2000 Å. It should be understood that other techniques may be used to form the FDSOI structure 340.

In step 214, within the semiconductor layer 313 disposed on the insulator layer 314 isolation regions 316 are formed which define the placement of a semiconductor active region 318 as represented in FIG. 3B. The regions 316 are insulator-filled to electrically isolate individual electrical devices such as the straddle gate FDSOI device 310. A local oxidized silicon (LOCOS) process that is known in the art may be used. Another process is shallow trench isolation (STI). The first step in forming STI regions is to form trenches in the FDSOI structure 340. Next, the semiconductive layer 313 is oxidized to round off the corners. Then, the oxide is removed during a water rinse. This is followed by a deposition of TEOS, which is polished back to the top surface 338 of the semiconductive layer 313 to form the STI regions 316. The polishing is done using conventional techniques, which are well-known in the art. It will be appreciated that the insulator-filled isolation trenches 316 may be formed in a later step in the method, rather than being formed as part

of the intermediate device shown in FIG. 3B. Other isolation techniques that are known in the art e.g. poly buffered LOCOS (PBL), polysilicon encapsulated local oxidation (PELOX) or the like may be used to isolate the straddle gate FDSOI device 310.

In step 216, a nitride topped gate is formed on the FDSOI structure as an intermediate stage of manufacture for the straddle gate FDSOI device 310. As shown in FIG. 3C, the intermediate gate device includes a gate dielectric 332 interposed between the lower surface 334 of a gate electrode 336 and an upper surface 338 of a portion of the FDSOI semiconductor structure 340. On top of gate electrode 336 a nitride layer 363 is formed to protect the gate electrode 36 during further processing. The gate dielectric 332 illustrated in FIG. 3C is a single-layer dielectric, however the gate dielectric could be a multi-layer dielectric as described above. The gate dielectric 332 may be made of suitable high-K gate dielectric materials, such as hafnium oxide (HfO_2), zirconium oxide (ZrO_2), tantalum oxide (Ta_2O_5) or the like. In this embodiment, gate dielectric 332 is made of HfO_2 . The exemplary gate dielectric 332 of HfO_2 may have a thickness of between 20 Å and 30 Å. The gate electrode 336 may be made of typical, well-known conductive materials, for example tungsten. An exemplary gate electrode 336 may have a thickness of between 500 Å and 700 Å. The nitride layer 363 may be made of typical, well-known nitrides, for example silicon oxynitride or the like.

Next in step 218, an oxidation process is conducted as represented in FIG. 3D. The oxidation may be performed for between five and sixteen seconds at a temperature of 800°C-900°C. An oxide layer 345 is formed having a thickness between 10 Å and 12 Å. The oxide layer may form on the gate (not shown). The oxidation process also forms a thin oxide layer 333 under the high-K material gate dielectric layer 335.

Next in step 220 and as shown in FIG. 3E, a nitride layer 347 is formed overlying the oxide layer 345 and the nitride topped gate. In one embodiment, the nitride layer 347 is a layer of silicon nitride which is deposited using rapid

thermal chemical vapor deposition. The nitride layer 347 may have a thickness of about 10 Å.

Then, in step 222 semiconductive spacers 349 are formed as shown in FIG. 3F to extend upward from the upper surface 352 of the nitride layer 347 and cover the sidewalls of the nitride layer 347 formed on the sidewalls of gate electrode 336. The semiconductive spacers 349 are formed straddling the gate electrode 336 and are used in the formation of the straddled gate, which will be further described below. In order to form the semiconductive spacers 349, a semiconductive material (not shown), e.g. polysilicon, or the like, is deposited on the nitride layer 347. The deposition produces a polysilicon layer (not shown) upon a top surface 352 of the nitride layer 347.

The polysilicon is etched with a suitable etch process, e.g. anisotropically. The polysilicon layer is reduced in size, leaving semiconductive spacers 349 of polysilicon as shown in FIG. 3F. The semiconductive spacers 349 may extend from a surface 352 of the nitride layer 347 to a height of between 800 Å and 1000 Å to be consistent with the height of the nitride topped gate. The polysilicon deposition may be performed, for example, by plasma enhanced chemical vapor deposition (PECVD) or sputtering techniques. The semiconductive spacers 349 may be implanted during source/drain implantation described below in a later step.

In step 224, the lightly doped source and drain regions 327 and 329 may be formed as shown in FIG. 3G using techniques well known in the art. The lightly doped source and drain regions 327 and 329 will form extension regions in a process further described below. One such technique is an extension perpendicular implant. An extension perpendicular implant is a relatively low energy, low concentration implant which is capable of producing the lightly doped source and drain regions 327 and 329. The total concentration of the extension implants may be, for example, between 1×10^{18} atoms/cm³ and 1×10^{20} atoms/cm³. An exemplary range of implant dose for the perpendicular implant is between 5×10^{13} and 1×10^{15} atoms/cm². The

extension perpendicular implants may be of the same material as the main perpendicular implant, or may alternatively include different materials.

Next, in step 226 a liner oxide layer 359 is formed over the structure as represented in FIG. 3H. The liner oxide layer 359 covers the exposed sidewalls of the semiconductive spacers 349 and the exposed surface of the nitride layer 347. The liner oxide layer 359 may be made of typical, well-known oxide materials, for example SiO_2 . The liner oxide layer 359 will act as a mask and prevent a metal layer used in a silicide formation described below from reacting with the sidewalls of the semiconductive spacers 349. An exemplary liner oxide layer 359 may have a thickness of about 30 Å.

After formation of the lightly doped source and drain regions 327 and 329 in step 228, the main source and drain regions 324, 326 are formed as shown in FIG 3I. The main source and drain regions 324, 326 may be formed by a main perpendicular implant, which will not affect the extension implant regions due to the liner oxide layer 359 acting as a mask. The main perpendicular implant is a relatively high energy, high concentration implant which is capable of producing the source and drain deep implant regions 324, 326. An exemplary range of concentration of these dopants is between 1×10^{20} and 5×10^{20} atoms/cm³. An exemplary range of implant dose for the perpendicular implant is between 1×10^{15} and 5×10^{15} atoms/cm². It will be appreciated that many alternative sequences or steps may be used to accomplish the implantation. It will be appreciated that a greater number of implants may be employed. Thus, extension regions 328, 330 and main source and drain regions 324, 326 are formed.

After implantation, the semiconductor device 310 may be subjected to rapid thermal annealing (RTA) at this time or at a later time. Exemplary RTA may be performed for between five and fifteen seconds at a temperature of 1,000 - 1,050°C.

Next in step 230, a nitride layer 357 is formed over the structure as represented in FIG. 3J. The nitride layer 357 covers the exposed surface of the liner oxide layer 359. The nitride layer 357 may be made of typical, well-

known nitride materials, e.g. silicon nitride (Si_3N_4), silicon oxynitride (SiON), or the like. An exemplary nitride layer 357 may have a thickness of about 30 Å.

Next in step 232, an anisotropic RIE etch is performed with a suitable etchant to remove portions of the nitride layer 357, the liner oxide layer 359, the semiconductive spacers 349, the nitride layer 347 and the oxide layer 345.

Additionally, the etchant removes the nitride layer 357, the liner oxide layer 359, the nitride layer 347 and the oxide layer 345 over the deep implant regions 324, 326 down to the surface 338 of the semiconductive layer 313. The etchant also removes a portion of the nitride layer 347 over the nitride topped gate exposing the top surface of nitride layer 363. The resulting structure as shown in FIG. 3K includes nitride spacers 357a, liner oxide layers 359a, the nitride layers 347a, semiconductive spacers 350 and the oxide layer 346. The nitride spacers 357a extend from a surface 362 of the oxide layers 359a to a height of between 700 Å and 900 Å just above the height of gate electrode 336. It will be appreciated that other suitable selective etching methods well-known in the art may be used.

Thereafter, in step 234, silicon and polysilicon layers 341 and 343, respectively, are thermally grown on the exposed surface 338 and the semiconductive spacers 350 as shown in FIG. 3L. The silicon and polysilicon layers 341 and 343 reach a height of between 200 Å and 400 Å. Thereafter, a metal layer is formed overlying the structure (not shown). The metal layer is formed by one of either sputtering, chemical vapor deposition (CVD), or evaporation. The metal layer may comprise any metal such as platinum, titanium, tantalum, nickel, cobalt, tungsten, and/or the like. In an exemplary embodiment, cobalt is used to form the metal layer. (Cobalt is preferred due to the fact that cobalt silicides have dopant diffusion and segregation coefficients that allow for formation of shallow conformal source and drain junctions, as illustrated in FIG. 1 as an alternative to the implantation method described above.)

After deposition of the metal layer in step 236, a heating cycle is performed. The heating cycle is used to react the portions of metal layer

which overlie the exposed surfaces of silicon and polysilicon layers 341 and 343. The resulting structure as illustrated in FIG. 3L remains.

If the metal layer comprises cobalt and the semiconductor layer 313 is silicon, then the cobalt reacts with the silicon within interface regions to form cobalt silicide (CoSi_2) including the source extension 328 and the drain extension 330 regions. Typical heat cycle temperatures for silicide/salicide formation range from 300 °C to 800 °C depending on the type of metal used. In all cases, silicided layers 342, 344, (also referred to as salicided regions in self-aligned cases) are formed within the source and drain regions 322 and the semiconductive spacers 350 via the heating cycle. Next as shown in FIG. 3M, all unreacted portions of the metal layer are removed via known etch techniques without removing the silicided layers 342, 344 and 356. For example, cobalt may be etched using an HCl and water isotropic etch solution.

It should be understood that metal layer deposited on the polysilicon layer formed over the gate may be of the same or a different metal than the metal layer deposited over the silicon layers 341, 343 and processed as described above in a self-aligning process to produce a salicide layer 356 (shown in FIG. 3 M).

In an alternative exemplary embodiment, the source and drain regions 322 can be formed using the process described below. An ion implant as described above may be used to dope the silicide regions 342, 344 with dopant atoms. Either boron, arsenic, or phosphorus may be used alone or in any combination as the dopant atoms. Therefore, either an n-type channel transistor or a p-type channel transistor may be formed. In one embodiment, the dopant atoms are ion implanted at an energy which places the dopant atoms only in the silicided regions 342, 344. Another heating cycle is used to drive the dopant atoms from the silicided regions 342, 344 into the substrate 313 to form the source and drain regions 322. In another embodiment, the ion implant of the dopant atoms may be performed at a high energy to ensure that the dopant atoms penetrate the silicided regions 342, 344 and form the source and the drain regions 322. It is important to note that the ion implantation of

the silicided regions 342, 344 to form the source and the drain regions 322 may be performed at any point in time in the process shown in FIGS. 3M-3O. A self-aligned process is preferred but is optional.

Now referring to FIG. 3N, an isolation layer, e.g. TEOS, is deposited on the intermediate structure including the nitride layer 363 on top of gate electrode 336 in step 238. The layer of TEOS reaches between 500 Å and 1000 Å above the nitride layer 363 of the nitride topped gate. Next, the TEOS is polished back to the top surface of the nitride layer 363 of the nitride topped gate. The result of this step is TEOS layer 365 that is illustrated on opposite sides of the gate device 310, respectively. TEOS layer 365 has overhangs with lower surfaces which are formed through contact with the nitride spacers 357a, the silicide caps 356 and the liner oxide layers 359a. The polishing is done using conventional techniques, which are well-known in the art.

In step 240 as illustrated in FIG. 3O, a selective etch of hot phosphoric acid is performed down to the gate electrode 336. The etchant removes a portion of the silicide caps 356, but leaves the semiconductive spacers 350 substantially unetched. All of the nitride layer 363 is removed. However, only portions of the oxide layer 359a, the nitride spacers 357a and the nitride layer 347 are removed. Thus, an upper surface of the polysilicon gate electrode 336 and a portion of the silicide capped semiconductive spacers 350 are left exposed. Thus, oxide layer 360, nitride spacers 358 and nitride layers 348 are formed. It will be appreciated that other suitable selective etching methods well-known in the art may be used.

Next, in step 242, and as illustrated in FIG. 1, contact plugs 80, 82 are formed. The contact plugs 80 are formed by masking the TEOS layer 365 to define the position of the contact plugs 80 and etching recesses in the TEOS layer 365 down to at least a top surface of the silicide layers 342, 344 above the source 322 and, if desired, the drain 322. Thus, TEOS layer 364 is formed. Then, a diffusion layer, e.g. titanium nitride (TiN), is deposited over the structure and polished back (not shown) resulting in diffusion barriers 386 as shown in FIG. 3P. The diffusion barriers 386 cover the exposed surfaces of

the openings formed in the TEOS layer 365 with a barrier layer about 50 Å and 150 Å thick.

Next, the remaining recesses are filled with the material selected for the contact plugs 80, 82. It will further be appreciated that the contact plugs 80, 82 may be formed at an earlier step in the method, rather than being formed as the last step in manufacturing the straddled gate FDSOI device 310. For example, the contact plugs 80, 82 may be formed any time after the TEOS layer 364 has been formed on the FDSOI structure 340. For example, after the TEOS layer 365 is deposited and polished back in step 238 to expose the nitride topped gate. Additional openings may be made in the TEOS layers 364 to allow electrical connection to be made with the source and drain regions, and with the gate electrode. Conventional well-known methods may be utilized to make openings therethrough, as described above.

The straddle gate FDSOI device of the present invention improves the off state (I_{off}) while maintaining a high on state (I_{on}). The first gate has a work function defined that is 0.3 – 0.5 eV greater than the work function of the second gate. The contact connects the first gate with the second gate (straddle gate) such that when the device is in the off state (I_{off}) a first channel region defined by the first gate and second channel region defined by the second gate define a long channel. However, when the device is in the on state (I_{on}), the first channel region defines a short channel due to the greater work function of the first gate.

Although the device 10 is illustrated as a straddled gate on an FDSOI structure, other devices such as electrically erasable programmable read only memories (EEPROMs), electrically programmable read only memories (EPROMs), flash EPROMs, thyristers, diodes, thin film transistors (TFTs), and the like may be formed on FDSOI structures as described above or on other types of substrates such as germanium-on-insulator(GOI) or semiconductor-on-insulator (SOI) and benefit from the features of the above described invention.

Although particular embodiments of the invention have been described in detail, it is understood that the invention is not limited correspondingly in

scope, but includes all changes, modifications and equivalents coming within the spirit and terms of the claims appended hereto.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
2223
2224
2225
2226
2227
2228
2229
2230
2231
2232
2233